

DICOM Correction Proposal

STATUS	Final Text
Date of Last Update	2025-04-02
Person Assigned	David Clunie
Submitter Name	Jörg Riesmeier <dicom@jriesmeier.com>
Submission Date	2024-07-02

Correction Number	CP-2442
Log Summary: Harmonize the meaning of Failure Reasons	
Name of Standard	
PS3.3 2025a	
Rationale for Correction:	
<p>It is proposed to harmonize the meaning of the Failure Reasons used for Storage Commitment and Media Creation Management, i.e., use the meanings that are defined for the DIMSE Status Codes in PS3.7 (if available and appropriate). If the meaning is identical, the same wording should be used.</p> <p>It is also proposed to make the following editorial changes to the standard text:</p> <ul style="list-style-type: none">• Use a consistent spelling (capitalization) throughout the standard text for the terms “SOP Class”, “Transaction UID”, “Storage Commitment request” and “Storage Commitment response”. This also includes PS3.4 and PS3.18.• Use “Media Storage Application Profile” or “Application Profile” throughout the standard text since these terms are defined in PS3.11 and PS3.10, respectively. “Media Application Profile” is not defined, but apparently used at various places as a synonym.	
Correction Wording:	

Change PS3.3 Section C.14.1 as follows

C.14.1 Storage Commitment Attribute Description

C.14.1.1 Failure Reason

The following ~~v~~Values and semantics shall be used for Failure Reason (0008,1197):

Enumerated Values:

0110H Processing ~~f~~Failure

A general failure in processing the operation was encountered.

0112H No such ~~object~~SOP instance

The specified SOP Instance was not available.

0213H Resource limitation

The SCP does not currently have enough resources to store the requested SOP Instance(s).

0122H Referenced SOP Class not supported

The specified SOP Class is not supported by the SCP.

0119H Class~~Instance~~ conflict

The specified SOP Class of the given SOP Instance did not correspond to the SOP ~~e~~Class registered for this SOP Instance at the SCP.

0131H Duplicate ~~t~~Transaction UID

The Transaction UID of the Storage Commitment ~~R~~requst is already in use.

Change PS3.3 Section C.22.1 as follows

C.22.1 Media Creation Management Module

C.22.1.1 Barcode Symbolology

The following Values and semantics may be used for Barcode Symbolology (2200,0006):

Defined Terms:

CODE128	ISO/IEC 15417:2000 Information technology - Automatic identification and data capture techniques - Bar code symbology specification - Code128
CODE39	ISO/IEC 16388:1999 Information technology - Automatic identification and data capture techniques - Bar code symbology specifications - Code 39
INTER_2_5	ISO/IEC 16390:1999 Information technology - Automatic identification and data capture techniques - Bar code symbology specifications - Interleaved 2 of 5 (also known as USS ITF 2/5, I-2/5, ITF 2of5)
HIBC	ANSI/HIBC 1-1996 Health Industry Bar Code (HIBC) Provider Applications Standard

Note

This doesn't list all the bar code symbologies in use (there are currently more than 400). Implementations supporting other symbologies can extend this list. Implementation-specific code values shall be defined in the Conformance Statement.

C.22.1.2 Execution Status

The following Values and semantics shall be used for Execution Status (2100,0020):

Enumerated Values:

IDLE	The SCP has created the m <u>M</u> edia e <u>C</u> reation m <u>M</u> anagement Instance, but it has not <u>yet</u> been yet scheduled.
PENDING	This m <u>M</u> edia e <u>C</u> reation m <u>M</u> anagement Instance is still scheduled for processing.
CREATING	This m <u>M</u> edia e <u>C</u> reation m <u>M</u> anagement Instance is being processed.
DONE	This m <u>M</u> edia e <u>C</u> reation m <u>M</u> anagement Instance has been successfully processed.
FAILURE	This m <u>M</u> edia e <u>C</u> reation m <u>M</u> anagement Instance failed to be processed.

Note

IDLE describes the status of a new ~~m~~Media ~~e~~Creation ~~m~~Management Instance (N-CREATE operation performed) for which the N-ACTION action has not been yet issued.

C.22.1.3 Execution Status Info

The following Values and semantics may be used for Execution Status Info (2100,0030):

Defined Terms:

CHECK_MCD_OP	The media creation request could not be accomplished since the device is not ready at this time and needs to be checked by an operator (e.g., covers/doors opened or device jammed).
CHECK_MCD_SRV	The media creation request could not be accomplished since the device is not ready at this time and needs to be checked by a vendor service engineer (e.g., internal component failure).
DIR_PROC_ERR	The DICOMDIR building process failed for some unspecified reason (e.g., mandatory Attributes or values missing).
DUPL_REF_INST	Duplicated Instances in the Referenced SOP Sequence (0008,1199).
INST_AP_CONFLICT	One or more of the elements <u>instances</u> in the Referenced SOP Sequence (0008,1199) are in conflict (e.g., the SOP Class specified is not consistent with the requested Application Profile).
INST_OVERSIZED	<u>The size of a</u> single <u>SOP</u> Instance size exceeds the actual media capacity.
INSUFFIC_MEMORY	There is not enough memory available to complete this request.
MCD_BUSY	Media creation device is not available at this time, but should become ready without user intervention (e.g., the media creation device's buffer capacity is full); the SCU should retry later.

MCD_FAILURE	Media creation device fails to operate; this may depend on permanent or transient hardware failures (e.g., robot arm broken, DVD writer failed) or because it has been disabled by an operator.
NO_INSTANCE	One or more of the SOP Instances in the Referenced SOP Sequence (0008,1199) are not available.
NOT_SUPPORTED	One or more of the Application Profiles, and/or SOP Classes, referenced in the Referenced SOP Sequence (0008,1199) are not supported by the SCP.
OUT_OF_SUPPLIES	No more supplies (e.g., blank media, labeling ink) are available for the media creation device; operator intervention is required to replenish the supply.
PROC_FAILURE	A general processing failure was encountered.
QUEUED	This Media Creation Management Instance is still in queue.
SET_OVERSIZED	The file-set size exceeds the actual media capacity, and the device is not capable of splitting across multiple pieces of media.
UNKNOWN	There is an unspecified problem.

Note

1. With respect to INST_OVERSIZED, DICOM media does not support spanning of Instances across volumes.
2. With respect to OUT_OF_SUPPLIES, This service is not supposed to provide detailed device status information, however sophisticated media creating devices can extend this table to return more information about the supply to be replenished. Implementation-specific code values shall be defined in the Conformance Statement.
3. For most of the above statuses, the SCU can obtain more details about the processing errors (e.g., what are the SOP Instances not available) by using Failure Reason (0008,1197) within the Failed SOP Sequence (0008,1198).

C.22.1.4 Failure Reason

The following Values and semantics may be used for Failure Reason (0008,1197):

Defined Terms:

- 0110H** Processing Failure; a general failure in processing the operation was encountered.
- 0112H** No such object/SOP Instance; one or more of the SOP Instances listed in the Referenced SOP Sequence (0008,1199) was not available.
- 0122H** Referenced SOP Class not supported; a media creation has been requested for a SOP Instance with a SOP Class that is not supported by the SCP.
- 0119H** Class-Instance conflict; the SOP Class of an Instance in the Referenced SOP ~~Instance~~ Sequence (0008,1199) did not correspond to the SOP ~~eC~~Class of the SOP Instance stored at the SCP.
- 0201H** ~~Media~~ Application Profiles conflict; one or more of the ~~Media~~ Application Profiles referenced in the Reference SOP Sequence (0008,1199) are in conflict (e.g., for the same request a STD-GEN-CD and a STD-GEN-DVD-JPEG is referenced).
- 0202H** ~~Media~~ Application Profile/Instance conflict; the SOP Class of an Instance in the Referenced SOP Sequence (0008,1199) did not correspond to a SOP ~~eC~~Class permitted for the requested or supported ~~Media~~ Application Profiles.
- 0203H** ~~Media~~ Application Profile/Compression conflict; the Application pProfile for an Instance in the Referenced SOP Sequence (0008,1199) specified lossy compression but Allow Lossy Compression (2200,000F) has a value of NO.
- 0204H** ~~Media~~ Application Profile not supported; media creation has been requested for an Application Profile that is not supported by the SCP.
- 0205H** Instance size exceeded; the size of a single SOP Instance ~~size~~ exceeds the actual media capacity.
- 0120H** Missing Attribute; a required Attribute (e.g., Patient ID) was not supplied; the missing Attribute(s) shall be listed in Failure Attributes (2200,000E).
- 0121H** Missing Attribute ~~v~~Value; a required Attribute Value (e.g., the Content Date for a Structured Report) was not supplied; the Attribute(s) with missing ~~v~~Values shall be listed in Failure Attributes (2200,000E).

Note

With respect to 0205H Instance size exceeded, DICOM media does not support spanning of SOP Instances across volumes.

See PS3.7 Section 9.1.5.1.4 for reference (unchanged)

9.1.5.1.4 Status

Indicates the status of the response. It may have any of the following values (see also Annex C):

- a. Success (0000H)
- b. **Refused: SOP Class not supported** (0122H) - Indicates that a different SOP Class than the Verification SOP Class was specified, which was not supported.
- c. Duplicate invocation (0210H) - Indicates that the Message ID (0000,0110) specified is allocated to another notification or operation.
- d. Mistyped argument (0212H) - Indicates that one of the parameters supplied has not been agreed for use on the Association between the DIMSE Service Users.
- e. Unrecognized operation (0211H) - Indicates that a different SOP Class than the Verification SOP Class was specified, which does not recognize a C-ECHO operation.

<i>See PS3.7 Section 10.1.1.1.8 for reference (unchanged)</i>

10.1.1.1.8 Status

This parameter contains the error or success notification for the operation. It shall be included by the performing DIMSE Service User in any response/confirmation. The following types of status may occur (see also Annex C):

- **Class-Instance conflict** (0119H) - the specified SOP Instance is not a member of the specified SOP class.
- Duplicate invocation (0210H) - the Message ID (0000,0110) specified is allocated to another notification or operation.
- Invalid argument value (0115H) - the event information value specified was out of range or otherwise inappropriate.
- Invalid SOP Instance (0117H) - the SOP Instance UID specified implied a violation of the UID construction rules.
- Mistyped argument (0212H) - one of the parameters supplied has not been agreed for use on the Association between the DIMSE Service Users.
- No such argument (0114H) - the event information specified was not recognized.
- No such Event Type (0113H) - the event type specified was not recognized.
- No such SOP Class (0118H) - the SOP Class was not recognized.
- **No such SOP Instance** (0112H) - the SOP Instance was not recognized.
- **Processing Failure** (0110H) - a general failure in processing the operation was encountered.
- **Resource limitation** (0213H) - the operation was not performed due to resource limitation.
- Success (0000H) - successful notification.
- Unrecognized operation (0211H) - the operation is not one of those agreed between the DIMSE Service Users.

<i>See PS3.7 Section 10.1.5.1.6 for reference (unchanged)</i>

10.1.5.1.6 Status

This parameter contains the error or success notification for the operation. It shall be included by the performing DIMSE Service User in any response/confirmation. The following type of status may occur (see also Annex C):

- Duplicate invocation (0210H) - the Message ID (0000,0110) specified is allocated to another notification or operation.
- Duplicate SOP Instance (0111H) - the new managed SOP Instance Value supplied by the invoking DIMSE Service User was already registered for a managed SOP Instance of the specified SOP Class.
- Invalid Attribute Value (0106H) - the Attribute Value specified was out of range or otherwise inappropriate.
- Attribute Value out of range (0116H) - the Attribute Value specified was out of range or otherwise inappropriate. The SCP will apply a default value or will not include the attribute in the created instance.

- Invalid SOP Instance (0117H) - the SOP Instance UID specified implied a violation of the UID construction rules.
- Missing Attribute (0120H) - a required Attribute was not supplied.
- **Missing Attribute Value** (0121H) - a required Attribute Value was not supplied and a default value was not available.
- Mistyped argument (0212H) - one of the parameters supplied has not been agreed for use on the Association between the DIMSE Service Users.
- No such Attribute (0105H) - the Tag for the specified Attribute was not recognized.
- Attribute list error (0107H) - one or more specified Attributes were not recognized and not included in the created instance.
- No such SOP Class (0118H) - the SOP Class was not recognized.
- Processing Failure (0110H) - a general failure in processing the operation was encountered.
- Resource limitation (0213H) - the operation was not performed due to resource limitation.
- Success (0000H) - successful operation.
- Unrecognized operation (0211H) - the operation is not one of those agreed between the DIMSE Service Users.
- Refused: Not authorized (0124H) - the DIMSE Service User was not authorized to invoke the operation.
- Failed (Status value is Service Class specific): no instance was created by the DIMSE Service User
- Warning (Status value is Service Class specific): the DIMSE Service User created an Instance but did not perform all specified operations